



8000 Whitepine Rd. Richmond VA 23237
www.sealeze.com

These tests were conducted by an independent laboratory.
Copies of the entire report are available upon request by
phone at 1-800-446-7325
or by e-mail at industrial@sealeze.com

Technical Data Sheet

Sealeze Brush Product No. SFB115BL100CF

Sealeze Static Control Brush with aluminum holder

Construction: Filament – 100% conductive nylon filament, 0.010" diameter, with chemically bonded carbon
Channel and Core Wire – galvanized steel
Holder – clear anodized aluminum

STATIC DECAY:

Target: Rate of decay shall be less than 2.0 seconds
Found: +1000v to +100v in 0.010 seconds
-1000v to -100v in 0.010 seconds
Method: Modification of EIA 541, Appendix F

SURFACE RESISTANCE OF BRUSH FIBERS:

ESDS541: Conductive Range $<1.0 \times 10^4$ ohms
Found: Average: 1.5783×10^2 ohms @ 1.0 volts
Method: ANSI/ESD STM11.11-2001

VOLUME RESISTANCE OF BRUSH FIBERS:

Target: Conductive Range $<1.0 \times 10^4$ ohms-cm
Found: Average: 3.8851×10^3 ohms-cm @ 1.0 volts
Method: ASTM D991

TWO-POINT RESISTANCE OF BRUSH FIBERS:

ESDS541: Conductive Range $<1.0 \times 10^4$ ohms
Found: Average: 1.5179×10^2 ohms @ 1.0 volts
Method: ANSI/ESD STM11.13-Draft Standard

TWO-POINT RESISTANCE OF MOUNTING BRACKET:

ESDS541: Static Dissipative $>1.0 \times 10^4$ - $<1.0 \times 10^{11}$ ohms
Found: Average: 5.4101×10^9 ohms @ 100 volts
Method: ANSI/ESD STM11.13-Draft Standard

CONTINUITY FROM MOUNTING BRACKET TO BRUSH FIBERS:

Target: Conductive Range $<1.0 \times 10^4$ ohms (No Standard)
Found: Average: 2.70×10^1 ohms @ 1.0 volts
Method: Prostat 801 Resistance System with 2 Leads

TRIBO CHARGE GENERATION (HIGHEST PEAK VOLTAGES):

Requirement: No Established Standard
Found: 10,240 volts to +1,720 volts @ 20%RH
10,240 volts to -1,455 volts @ 50%RH
Reference: Static Sensor Placement near Substrate after Contact¹

ESD INSIDE SHELF LIFE (Storage without use)

Requirement: 5 Years
Found: Indefinite
Reference: Contains no antistats

Note: ¹Results may vary from location to location. ESDS541 = ANSI/ESD S.541-2003 Form: ESD2-05/9/04

Since different levels of ESD protection are required for different devices, all users should perform their own tests to prove the suitability of the static control brush material for specific applications. User assumes all liability regarding damage or loss arising from use of products. User shall determine the applications of these materials for the intended application(s), and assumes total liability in the event of aforementioned damages.